
Pneumatic Swing Clamp

block-type, for adjustable magnetic sensors double acting, max. operating pressure 7 bar



Advantages

- Compact design
- Easy adjustment of switching point positions
- Diverse mounting possibilities
- 5 standard sizes are available
- optionally with thread connection or for manifold mounting with O-ring sealing

Application

Pneumatic swing clamps are used for applications which require only low clamping forces. The installed magnetic piston allows monitoring of clamping and unclamping position.

Description

When pressurising the element, the clamping arm swings and lowers by 90° to the clamping position and then lowers to the clamping point. The position monitoring gives the required information regarding the position of the piston, but not regarding the position of the clamping arm. Monitoring is made by electronic sensors (see accessory) which detect the magnetic field of the magnetic piston. The switching points can be continuously adjusted by displacement of the magnetic sensors.

Special features

When adjusting the clamping screw it has to be considered that for the swing motion a part of the total stroke is required.

Make sure that the swing motion can be effected without any interference.

When using special clamping arms with other lengths, the corresponding operating pressures as shown in the clamping force diagram must not be exceeded.

Pneumatic accessories

see data sheet J 7.400.

Installation

The block-type offers universal mounting possibilities.


Material

The swing clamps are supplied in corrosion resistant quality. Guide bushing, housing, piston, and flange are made of hardcoated aluminium. The piston rod is made of corrosion resistant steel.

Important notes

Operating of these pneumatic elements has to be effected with an additional service unit in order to guarantee that the clamping elements are supplied with correctly prepared compressed air.


Operating conditions, tolerances and other data see data sheet A 0.100.




Versions


- Versions with pipe thread (Figure at the left-hand side) see page 2
- Manifold mounting with O-ring sealing Version K (Figure in the centre), see page 3
- Manifold mounting with O-ring sealing Version B (Figure at the right-hand side), see page 3

Connection example



Threaded body Technical data • Accessories







Piston Ø	[mm]	20	32	40	50	63
Pistron rod Ø	[mm]	8	12	16	20	25
Stroke to swing	[mm]	7.5	9.5	17	18	23
Stroke to clamp	[mm]	7	9	15	15	18
Pulling force at 4 k	bar [N]	105.5	276.4	422.2	659.7	1050.5
*air 51	bar [N]	131.9	345.5	527.7	824.6	1313.1
	oar [N]	158.3	414.6	633.3	989.6	1575.8
Min. operating press				3		
Max. operating press	sure [bar]			7		
Angle of rotation	[°]			$90^{\circ} \pm 2^{\circ}$		
Weight	[kg]	0.35	0.8	1.3	2.0	3.33
a	[mm]	120.5	143	189.5	203.5	239.5
b	[mm]	76	94.5	120.5	130	150
C	[mm]	55.5	72	99	104	118
f	[mm]	M5	M5	G 1/8	G 1/8	G 1/4
g	[mm]	M5	M5	G 1/8	G 1/8	G 1/4
h	[mm]	41	59.5	71.5	76	80
i	[mm]	53.5	63	88	95	100
j	[mm]	17	20	19	17.5	18
□k	[mm]	12	16	20	25	30
	[mm]	103.5	119.5	159	164	197
m	[mm]	22	28	42	44	58
Øn	[mm]	14	24	30	38	42
0	[mm]	54	68	80	90	106
р	[mm]	35	52	60	70	85
q	[mm]	M4	M6	M8	M12	M10
r	[mm]	40	55	64	72	86
S	[mm]	22	38	42	48	66
t	[mm]	25	40	46	50	70
Øu	[mm]	5.5	6.5	6.5	8.5	8.5
V	[mm]	10	12	12	15	15
W	[mm]	M8	M8	M8	M10	M10
Clockwise rotation		4070400	4074400	4075400	4070400	4077400
Part no.	4 - 4 :	1873 106	1874 106	1875 106	1876 106	1877 106
Counterclockwise ro	tation	1873206	1874206	1875206	1876206	1877206

^{*} Effective clamping force see diagram (page 3, column 1)


Seat of clamping arm






Swing clamp	Ø d + 0.05	□ k	h	q	
1873 X06	7.85	12	9	M 4	
1874 X06	11.85	16	15	M 6	
1875 X06	15.85	20	19	M 8	
1876 X06	19.85	25	18	M 12	
1877 X06	24.85	30	25	M 10	

Clamping arm



Swing clamp	а	b	С	Ø d + 0.05	f	g min.	g max.	□k	Part no.
1873 X 06	54	7	42	7.85	M 4	8	28	12	0187326
1874X06	68	10	52	11.85	M 6	12	27	16	0187426
1875 X 06	78	12	58	15.85	M 6	12	42	20	0187526
1876X06	90	14	68	19.85	M 8	15	42	25	0187626
1877 X06	110	18	80	24.85	M10	19	56	30	0187726

Clamping arms for special versions



Swing clamp	а	b	Ø d + 0.05	□k	Part no.
1873 X 06	62	7	7.85	12	3548355
1874 X06	72	10	11.85	16	3548356
1875 X06	95	12	15.85	20	3548357
1876 X06	116	14	19.85	25	3548353
1877 X06	143	18	24.85	30	3548358


Contact bolt, dome head





Swing clamp	а	b	f	R	SW	Part no.
1873 X06	32.5	30	M 4	15	7	3614 141
1874 X06	33.5	30	M 6	20	10	3614137
1875 X06	48.5	45	M 6	20	10	3614138
1876X06	50	45	M 8	20	13	3614139
1877 X06	66.5	60	M 10	35	17	3614140


Manifold mounting with O-ring sealing Technical data


Effective clamping force











Swing clamp

Clockwise rotation		1873106X	1874 106X	1875 106X	1876106X	1877 106X
Counterclockwise rota	ation	1873 206X	1874206X	1875 206X	1876 206 X	1877 206 X
Piston Ø	[mm]	20	32	40	50	63
Piston rod Ø	[mm]	8	12	16	20	25
a	[mm]	120.5	143	189.5	203.5	239
b	[mm]	76	94.5	120.5	130	150
C	[mm]	55.5	72	99	104	118
е	[mm]	16	28	36	44	58
h	[mm]	41	59.5	71.5	76	80
i	[mm]	53.5	63	88	95	100
j	[mm]	20	20	19	17.5	18
k	[mm]	39	53	60	72	86
	[mm]	_	14	20	20	20
0	[mm]	54	68	80	90	106
p	[mm]	35	52	60	70	85
r	[mm]	40	55	64	72	86
S	[mm]	22	38	42	48	66
t	[mm]	25	40	46	50	70
Øu	[mm]	5.5	6.5	6.5	8.5	8.5
V	[mm]	10	12	12	15	15
W	[mm]	M8	M8	M8	M10	M10
max. Ø x	[mm]	5	5	5	5	5
Dimensions O-ring	[mm]	7x1.5	7x1.5	7x1.5	7x1.5	7x1.5
Part no., spare O-rir O-rings are included in		3000 342 Other dimens	3000 342 sions see page	3000342 \Rightarrow 2.	3000342	3000342

Order:

Please add the corresponding identification letter to the **Part no.** of the required pneumatic block-type swing clamp: ${\bf K}$ or ${\bf B}$

Example of ordering:

Pneumatic block-type swing clamp 1875-106 with air supply on the broad side

Part no. 1875-106 K

Compared with traditional reed switches the electronic magnetic sensors offer the following

- Indifference to shock and vibration
- Bounce-free output signal
- Only one switching point
- Wear resistant
- Protection against reverse battery
- Protected against short circuits

Electric connection is made as per traditional inductive proximity switches; up to four magnetic sensors can be connected in series.


Minimum distance of the switching points: 6 mm.

Important notes


Steel can influence the magnetic field of the magnetic piston and thereby the position of the switching points. If there is the same influence for each stroke (e.g. because of adjoining steel components) it can be compensated by displacing the magnetic sensors. But if the influence differs from stroke to stroke, as e.g. in the case of swarf, a cover has to be provided 30 mm over the magnetic sensors. Covers have to be provided to protect the cylinders against ferritic swarf.

Further information about voltage supply for position controls see data sheet A 0.120.


Electronic magnetic sensor




Temperature curve




Connecting cable with right angle plug



Connecting scheme





Technical data

Cylinder body material Voltage Residual ripple Current load I_{LOAD}

Current consumption Voltage drop (max. load) Protected against short circuits Protection against reverse battery

Switching frequency Switching hysteresis Protection as per 40050 Environmental temperature

Plug connection LEĎ

Cable, length of cable Output (interlock) Part no.

Electronic magnetic sensor

aluminium black lacquered	
10 – 30 V DC	10 – 30 V [
max. 10%	
200 mA – up to 50 °C	
150 mA – at 75 °C	
100 m∆ = at 100 °C	

 $< 15 \,\mathrm{mA}$ < 2 Vyes installed 1 kHz

3 mm IP 67 –25 °C up to +100 °C

M8 plug no

pnp 3829234 ngn 3829240

Connection cable with right angle plug

DC

IP 67 –25 °C up to +90 °C M8 plug Voltage (green) Function display (yellow) PUR, 5 m ngn pnp

3829099 3829124

Range of magnetic signal

Further accessory

see data sheet G 2.140

- Pin-and-socket connector
- Y-distributor
- Reversing plug
- Voltage regulator

Swing stroke	Unclamping position	× \$
Clamping stroke Swing stroke	Monitored clamping position	×
•		

Type	≈ x [mm]
1873 X06	4
1874 X06	4
1875 X06	5
1876 X 06	6
1877 X06	7